

# VESTA-047NNZ-433

HSGW-4G DEDUCT ZW&EXTERNAL ANTENNA



## 320-zone IP + 4G home security center via radio

### 4G

- VESTA IP + 4G home security center for 320 zones via radio
- RF 433-F1 devices
- TCP/IP and 4G connectivity (optional WiFi pin)
- Bidirectional RF up to 2 km
- Integral solution with remote management
- Domotics and live supervision
- 8 partitions
- Supports external batteries (DEM-7M-BACKUP, DEM-8M-BACKUP and DEM-9M-BACKUP)
- Includes Mini USB quick connector for external organic battery
- Sending reports via CID/SIA, Email, SMS and Push
- iOS and Android App and web browser
- Compatible with Google Home and Alexa



Reference / Model	VESTA-047NNZ-433 / HSGW-4G DEDUCT ZW&EXTERNAL ANTENNA
320 radio zones	
320 users	
8 partitions	
TCP/IP and 4G communication (optional WiFi pin)	
Incorporates 4G module	
Supports RF 433-F1 devices	
Reporting methods: CID/SIA, Email, SMS, Push Notification	
Programming methods: Web and App	
Live visual verification	
Home automation	
Energy management	
24/7 emergency monitoring	
Remote management	

# VESTA-047NNZ-433

HSGW-4G DEDUCT ZW&EXTERNAL ANTENNA



## 320-zone IP + 4G home security center via radio

Reference / Model	VESTA-047NNZ-433 / HSGW-4G DEDUCT ZW&EXTERNAL ANTENNA
Built-in siren	
RF Frequency: 433MHz	
4G Frequency: 850/900/1800/1900MHz	
Power supply: 12V, 1A	
Backup battery: 7.2V, 1100mAh, Ni-mH, rechargeable	
Battery life of 13 hours	
Ready to support high capacity external battery( <b>DEM-7M-BACKUP</b> , <b>DEM-8M-BACKUP</b> and <b>DEM-9M-BACKUP</b> )	
Includes Mini USB quick connector for external organic battery connection	
Operating temperature from -10°C ~ +45°C	
Relative humidity: Up to 85% (non-condensing)	
Dimensions: 140 (W) x 150 (H) x 42 mm	
VESTA radio control panel is compatible with Google Home and Alexa	
Includes Mini USB quick connector for external organic battery connection	

