

Cellular alarm system 4G VESTA battery-powered or battery/external source



- 50 zone compact control panel via VESTA radio
- Self-contained panel powered by batteries or battery/external power supply
- MicroUSB port for quick programming
- Allows external SMA-type LTE antennas
- Compatible with all 868-F1 RF devices (2 km in open field)
- GPRS/3G/4G LTE communication
- Sending reports via CID/SIA, Email, SMS and Push
- Configuration by APP smarthomesec or through the built-in keyboard
- LCD screen for viewing status and settings
- Up to 6 users
- Supports up to 6 PIRcam
- Incorporates 100dB siren
- Works with alkaline batteries type D (included)
- Autonomy of up to 1.4 years
- EN50131 Grade 2



Reference / Model	VESTA-068N / VESTA-068N
--------------------------	--------------------------------

specs

Autonomous panel powered by batteries or external battery
 It can operate with external batteries or power supplies (it has a DC Jack input)
 It has a MicroUSB port to be able to carry out quick programming with the PC or even carry out updates in less than 2 minutes
 Allows external SMA-type LTE antennas
 GPRS/3G/4G LTE communication flexibility, allowing seamless communications at remote sites
 Battery life: 1 year and 2 months, with test transmissions every 6 hours
 External battery life (optional): 1 year with 24/7 cloud connection
 Up to 50 zones via radio with a range between device and control panel of up to 2 km
 Compatibility with the large catalog of more than 50 F1 devices: keypads, sirens, smoke sensors, PIR detectors, PIRCAMS, temperature sensors, door contacts, perimeter detectors, vibration sensors, etc.
 Supports 6 indoor and outdoor PIRCAMS, allowing users and monitoring stations to visually verify the alarm
 Supports smoke detectors and water sensors, for 24-hour protection against fire damage and water leaks
 Supports temperature sensors for protection against high and/or low temperatures with the possibility of setting ranges
 Allows total configuration from keyboard and LCD screen incorporated in the control panel
 Schedule automatic arming/disarming by calendar
 Built-in 100dB siren to give an immediate warning, with the possibility of adding internal and external sirens F1
 Extreme convenience and flexibility in event and photo communication methods to ARC (MANITOU, encrypted MANITOU, CID, SIA)
 Possibility of remote access to CRA for quarterly tests through a WAKE UP command
 Grade 2 Certificate
 With VESTA's free SmartHomeSec app you can immediately receive photo alarm and event notifications. In addition, from the installer section, you can fully configure your control panel in less than 10 minutes