

## Outdoor siren via radio

### ✓ GRADE 2

- VESTA outdoor siren via radio
- Sound power of 107dB at 1 meter
- Adjustable volume by DIP switch
- Tamper tamper
- It works with batteries or connected to the AC network
- Allows remote configurations



#### Reference / Model

**VESTA-207N / BX-23B-AC**

#### Specifications

107dB output power at 1 meter  
F1 RF technology accelerates the signal transmission speed and increases the communication range  
RF frequency, 868MHz  
Four programmable siren duration options  
Adjustable volume via DIP switch  
Differentiated sounds for each type of alarm: intrusion alarm, fire alarm and water leak alarm  
Programmable strobe activation  
Differentiated alarm sounds for fires and burglaries  
It works with batteries or with alternating current  
Meets CE requirement  
IP56 waterproof and dustproof housing  
Audible arming / disarming, door chime and low battery status notification  
Periodic monitoring signals to verify system integrity and troubleshoot  
Tamper protection prevents unauthorized removal or tampering  
Low battery detection  
Allows remote configurations  
Power supply: 4 1.5V alkaline batteries or from alternating current  
Battery life of up to 4 years  
It also works connected to the AC network  
-25 ° C ~ + 60 ° C operating temperature  
Relative humidity up to 85% (non-condensing)  
Dimensions: 205 (W) x 317 (H) x 83 mm  
Complies with EN50131-4 / EN50131-5-3 Grade II, Environmental Class IV