

# VESTA-112N-SF1

HYB-1-S0-QT-E-SF1 868



## 4G+IP hybrid alarm system VESTA



GRADE 3

4G



- VESTA hybrid control panel with V-MAX BUS protocol
- Compatible with HD transmission devices (PIRCAMS) and SF1 bidirectional audio
- 4G (LTE) and IP (Ethernet) connectivity
- 16 expandable wired zones
- Up to 640 zones (128 wired and BUS + the rest via radio)
- 8 partitions and 240 users
- 1 PGM output (siren)
- Up to 4 VESTA-114/VESTA-125 keypads
- Configuration by smarthomesec APP
- EN50131 Grade 3



### Reference / Model

**VESTA-112N-SF1 / HYB-1-S0-QT-E-SF1 868**

4G (LTE) model

Amplified fast connection for external GPRS antenna (not included, VESTA-275 or VESTA-276 recommended)

Advanced automation and home automation management functions

Latest communication technologies: built-in IP module, plus 4G LTE

Built-in SF1, the fastest radio transmitter on the market

Triple RF transmission speed

Supports HD streaming devices (PIRCAMS) and SF1 two-way audio

Built-in F1 868Mhz radio receiver compatible with all F1 devices in the catalogue (2 km in open field)

Allows up to 16 wired zones on board expandable via zone expanders

Allows both wired and F1 radio zones (640 zones in total)

Up to 8 areas

Allows up to 4 wired keypads

# VESTA-112N-SF1

HYB-1-S0-QT-E-SF1 868



## 4G+IP hybrid alarm system VESTA

Reference / Model	VESTA-112N-SF1 / HYB-1-S0-QT-E-SF1 868
	Up to 240 users
	1 siren output, plus 1 simultaneous voltage-free output
	Full programming in less than 10 minutes from the web and SmartHomeSec app
	Flexibility of wiring and selection of resistance values for each zone
	Integration with DAHUA IP cameras
	Compatibility with all F1 devices for automatic control of your installation (relays, sockets, sensors, etc.)
	Supports indoor and outdoor PIRCAMS, allowing users and central stations to visually verify the alarm
	Programming of up to 100 automatic rules (automatic watering, presence simulation, control of any device by calendars, auto-arming, etc.).
	Extremely convenient and flexible methods of communicating events and photos to the
	ARC (MANITOU, encrypted MANITOU, CID, SIA, FTP, HTTP).
	3A power supply
	Voltage for BUS module and wired zones: 13.56V
	Grade 3 certified
	With VESTA's SmartHomeSec application you can remotely control and manage both your security and video surveillance system and smart home devices.
	VESTA's hybrid control panel is Google Home and Alexa compatible
	USB port for adding WiFi, ZigBee or Z-Wave connectivity (see related products)
	Integration with Fibaro automatic devices (Fibaro Dimmer 2, Roller Shutter 3, Smart Module, Single Switch 2)