

VESTA 1 digital input / output module



- VESTA 1 digital input / output module
- Integrate wired devices into wireless networks
- NO / NC inputs
- Power: 5V ~ 12V DC
- Backup battery: 3 CR123 batteries or 2 L91 AA batteries
- 4.7 year battery life (CR123), 3.5 years (L91)



Reference / Model	VESTA-028 / DIO-52-F1
Features	
One digital input and one digital output	
Dry contact input forms NO (normally open) or NC (normally closed) loops	
Converts the device connected to the digital input into an event trigger	
Turn the device connected to the digital output into an event responder	
Obtains data from and activates hard-wired or hard-to-reach remote devices	
Establish reliable and fast communication between the control system and remote devices	
LED status indicator	
CE conformity	
Specs	
RF frequency: 868MHz	
1 digital input	

VESTA 1 digital input / output module

Reference / Model	VESTA-028 / DIO-52-F1
1 digital output (maximum load from 2A at 30V DC or 0.5A at 125V AC)	
Power: 5V ~ 12V DC	
Backup battery: 3 CR123 batteries or 2 L91 AA batteries	
4.7 year battery life (CR123), 3.5 years (L91)	
-10 ° C ~ + 45 ° C operating temperature	
Relative humidity up to 85% (without condensation)	
Dimensions: 111 (W) x 91 (H) x 29mm	