

Cellular alarm system 4G VESTA battery-powered or battery/external source

 **2G**  **3G**  **4G**

- 50 zone compact control panel via VESTA radio
- Self-contained panel powered by batteries or battery/external power supply
- MicroUSB port for quick programming
- Allows external SMA-type LTE antennas
- Compatible with all 868-F1 RF devices (2 km in open eld)
- GPRS/3G/4G LTE communication
- Sending reports via CID/SIA, Email, SMS and Push
- Con guration by APP smarthomesec or through the built-in keyboard
- LCD screen for viewing status and settings
- Up to 6 users
- Supports up to 16 PIRcams
- Incorporates 100dB siren
- Works with alkaline batteries type D (included)
- Autonomy of up to 1.4 years
- EN50131 Grade 2



Reference / Model

VESTA-068N / VESTA-068N

spe cs

Autonomous panel powered by batteries or external battery

It can operate with external batteries or power supplies (it has a DC Jack input)

It has a MicroUSB port to be able to carry out quick programming with the PC or even carry out updates in less than 2 minutes

Allows external SMA-type LTE antennas

GPRS/3G/4G LTE communication, allowing seamless communications at remote sites

Battery life: 1 year and 2 months, with test transmissions every 6 hours

External battery life (optional): 1 year with 24/7 cloud connection

Up to 50 zones via radio with a range between device and control panel of up to 2 km

Compatibility with the large catalog of more than 50 F1 devices: keypads, sirens, smoke sensors, PIR detectors, PIRCAMs, temperature sensors, door contacts, perimeter detectors, vibration sensors, etc.

Supports 6 indoor and outdoor PIRCAMs, allowing users and monitoring stations to visually verify the alarm

Supports smoke detectors and water sensors, for 24-hour protection against re damage and water leaks

Supports temperature sensors for protection against high and/or low temperatures with the possibility of setting ranges

Allows total con guration from keyboard and LCD screen incorporated in the control panel

Schedule automatic arming/disarming by calendar

Built-in 100dB siren to give an immediate warning, with the possibility of adding internal and external sirens F1

Extreme convenience and exibility in event and photo communication methods to ARC (MANITOU, encrypted MANITOU, CID, SIA)

Possibility of remote access to CRA for quarterly tests through a WAKE UP command

Grade 2 Certi cate

With VESTA's free SmartHomeSec app you can immediately receive photo alarm and event noti cations. In addition, from the installer section, you can fully con gure your control panel in less than 10 minutes