

VESTA-027

HWC-1B-F1



Radio wiring converter

✓ GRADE 2

- Wired to wireless zone converter for VESTA system
- Converts 9 wired zones into wireless zones
- Allows power supply to detectors
- Terminal connection
- Allows resistance values between 1K and 10K
- Self-adjusting to the wired resistance
- Tamper tamper
- Back-up battery included: AAA Ni-Mh rechargeable battery pack, 750 mAh
- EN50131 Grade 2 certified



Specifications

Reference / Model	VESTA-027 / HWC-1B-F1
	Converts 9 wired zones to wireless technology
	Compact and lightweight for easy installation
	Excellent stability with high sensitivity
	4-pin terminal block for power supply
	14-pin terminal block for all 9 zones
	Tamper protection
	Low battery notification

Radio wiring converter

Reference / Model**VESTA-027 / HWC-1B-F1**

Periodic supervisory signals to verify system integrity

LED indicator

Ideal for retrofitting existing hardwired security systems

EN50131 certification (Grade 2)

RF Frequency: 868MHz

Power supply: 12V, 1A

Allows resistance values between 1K and 10K

Self-adjusting to the wired resistor

Battery backup included: Rechargeable AAA Ni-Mh battery pack, 750 mAh

Operating temperature from -10°C ~ +45°C

Relative humidity up to 85% (non-condensing)

Dimensions: 163 (W) x 105 (H) x 30 mm