

VESTA-017N

RC-15-F1-2W



VESTA bidirectional radio push button

GRADE 2

- VESTA bidirectional radio push button with 4 buttons
- Arm/disarm, start and panic
- Suitable for security and home automation
- Operates with 1 CR2032 3V lithium battery
- Battery life of 8 years
- UL1023
- EN50131 Grade 2, ClassII



Reference / Model

VESTA-017N / RC-15-F1-2W

Bidirectional communication

Allows control of the security system

Four buttons: Arming / Disarming / Home / Panic

Bidirectional confirmation of actions via LEDs

Durable, scratch-resistant buttons

Lightweight keychain design

Low battery detection

Suitable for security and home automation installations

RF Frequency: 868MHz

Power supply: 1 CR2032 3V lithium battery

Battery life of 8 years

Operating temperature from -10°C ~ +45°C

Relative humidity up to 85% (non-condensing)

VESTA-017N

RC-15-F1-2W



VESTA bidirectional radio push button

Reference / Model

VESTA-017N / RC-15-F1-2W

Dimensions: 65 x 38 x 15 mm

UL1023 compliant

EN50131 Grade 2, ClassII certified