

# VESTA-030

RP-29-F1



## VESTA radio extender / repeater

### ✓ GRADE 2

- VESTA radio extender / repeater
- Extends the communication range between the sensors and the Control panel
- Rechargeable backup battery
- Tamper proof
- Includes 220V power supply
- Grade 2



#### Reference / Model

VESTA-030 / RP-29-F1

#### Features

Extends the radio signal of any PIRCAM

Extends communication range between alarm gateway and sensors

Repeaters can repeat each other

Intelligent signal filtering eliminates repetitive signal transmissions

Includes Battery Backup: Rechargeable AAA Ni-Mh battery pack, 750 mAh

Tamper protection

Compatible with VST-862-F1 series detectors

Four LEDs show power, installation, transmit, and receive status

Periodic supervisory signals to verify system integrity

Suitable for residential and commercial use

EN50131 Grade 2 certified

# VESTA-030

RP-29-F1



## VESTA radio extender / repeater

**Reference / Model**

**VESTA-030 / RP-29-F1**

### Specifications

RF frequency: 868MHz

Power: 12V, 1A

Battery back-up included: Rechargeable AAA Ni-Mh battery pack, 750 mAh

Battery life of up to 15 hours

-10 ° C ~ + 45 ° C operating temperature

Relative humidity up to 85% (without condensation)

Dimensions: 186 x 130 x 30mm

Grade 2