

Magnetic via recessed radio



- Magnetic via recessed radio
- Door / window opening / closing supervision
- LED indicator for failure and test
- Powered by 1 3V CR2 lithium battery
- 10 year battery life

**Reference / Model**

VESTA-031 / RDC-1-F1

Features

Monitors the opening / closing of doors and windows

Powered by a pre-installed long-lasting battery

Elegant design

Simple and flexible installation

Random supervisory signals to verify system integrity and troubleshooting

LED serves as fault indicator and test mode

Low battery detection

Specs

RF frequency: 868MHz

Power: 1 3V CR2 lithium battery

Battery life of up to 10 years

Magnetic via recessed radio

Reference / Model**VESTA-031 / RDC-1-F1**

-10 ° C ~ + 45 ° C operating temperature

Relative humidity up to 85% (without condensation)

Contact dimensions: 69 x 39 x Ø19 mm

Magnetic dimensions: Ø22 x 12 mm