

VESTA-047NNZ-SF1

PKB1HSGWM8B4GSL02



IP + 4G home security center for 640 wireless zones



- VESTA home security center
- 640 wireless zones
- 240 users, 8 partitions
- Supports RF 868-F1 devices (up to 2 km)
- Compatible with PIRCAMS HD and SF1 bidirectional audio
- TCP/IP and 4G connectivity (optional WiFi pin)
- Integral solution with remote management
- Domotics and live supervision
- Sending reports via CID/SIA, Email, SMS and Push
- iOS and Android App and web browser
- Compatible with Google Home and Alexa
- EN50131 Grade 2



Reference / Model	VESTA-047NNZ-SF1 / PKB1HSGWM8B4GSL02
640 radio zones	
240 users	
8 partitions	
TCP/IP and 4G communication (optional WiFi pin)	
Incorporates 4G module	
Supports RF 868-F1 devices	
Supports HD streaming devices (PIRCAMS) and SF1 two-way audio	
Reporting methods: CID/SIA, Email, SMS, Push Notification	
Programming methods: Web and App	
Live visual verification	
Home automation	
Energy management	
24/7 emergency monitoring	

VESTA-047NNZ-SF1

PKB1HSGWM8B4GSL02



IP + 4G home security center for 640 wireless zones

Reference / Model

VESTA-047NNZ-SF1 / PKB1HSGWM8B4GSL02

Remote management

Built-in siren

RF Frequency: 868MHz

Power supply: 12V, 1A

Includes Mini USB quick connector for external organic battery connection

Operating temperature from -10°C ~ +45°C

Relative humidity: Up to 85% (non-condensing)

Dimensions: 140 (W) x 150 (H) x 42 mm

EN50131 Grade 2 certified, Environmental Class II

VESTA radio control panel is compatible with Google Home and Alexa

Integration with Z-Wave automatic devices from Aeotec or Fibaro (Fibaro Dimmer 2, Roller Shutter 3, Smart Module, Single Switch 2) via not included dongle module **VESTA-240** (ZW-DONGLE)